



Unicable II™

2-way Combiner, 950-2300MHz

IDLU-UCM102-00020-OPB

Item: 5388



This Unicable™ combiner supports the combination of two RF signals. It enables control signals and DiSEqC commands sent from the Set Top Box to the LNB as well as DiSEqC commands sent from the LNBs to the Set Top Box. This high-quality Unicable™ combiner features low insertion loss, high RF isolation between the input ports and allows greater flexibility in single home or MDU installation scenarios. Typically, the combiner would be installed at a central location (i.e. roof's attic) to combine signals of two Unicable LNBs or Multiswitches to one coax cable stretched inside the house/apartment to a Set Top Box.

Main Features:

- Bi-directional signal distribution
- Low insertion loss
- High isolation between input
- Protective diodes for DC isolation at each input port



Technical data

Frequency range	950 MHz ~ 2300 MHz
Inputs	2x F-type, female
Output	1x F-type, female
Insertion loss	4 dB max.
Isolation between ports	18 dB min.
Input return loss	10 dB max.
Output return loss	10 dB max.
DC & 22 kHz pass from Output to Input	Yes
Impedance	75 Ω
Operating temperature	-30° C ~ +60° C
Weight	39 g
Dimensions (W x D x H)	58.5 mm x 50 mm x 16.3 mm

Logistical info

Quantity per carton	150
Carton dimensions (W x D x H)	42.4 cm x 38.8 cm x 62 cm
Carton weight	6.7 kg

